2009

PRODUCTION AND OPERATIONS MANAGEMENT

Paper: 202

Full Marks - 70

Time - Three hours

The figures in the margin indicate full marks for the questions.

Answer any five questions.

- 1. (a) What is job shop production? What are its characteristics, advantages and limitations? Suggest strategies to overcome some of its limitations.
 - (b) Indicate how and why each of these factors is important to the successful design and operation of a super market.

 6
 - (i) Layout of the store

[Turn over

- (ii) Location
- (iii) Capacity planning.
- (a) What do you understand by "Plant Design"? Discuss the various factors to be considered in deciding the location of a car manufac turing plant.
 - (b) An assembly line must be established to include the tasks as given in the table.

Task	Task time	Predecessors
ř	(in sec)	
A	120	none
В	50	Α
С	40	В
D	80	C, F
E	100	Α
F	20	Ε
G	90	Н
Н	60	A
I	30	A
J	60	D, G, I
		e = ==

2/25(2) POM 202

a sequence diagram for the

the line to a 120-second cycle is the minimum number of required ?

the longest operation time (LOT) balance the line to a 120-second

What is the efficiency of the line?

- (a) What do you understand by productivity? In what units can it be expressed? Explain the difference between production and **Productivity.**
- (b) What is the difference between method study and work measurement? What steps are followed for doing a method study of job process ?
- (a) What is ABC, FSND and VED analysis? What are the basic steps in implementing them ?

№(2) POM 202

Turn over

- parts of a machine for its annual top ordering one-month usage at a part costs Rs. 20. The ordering consist Rs.15 and the carrying charges of the average inventory per year.

 You have been asked to suggest economical purchasing policy company. What advice would you offer how much would it save the company year?
- 5. (a) What is inspection? What is the difference between inspection and qualification?
 - (b) The following are the inspection results 20 lots of magnets, each lot of being of 75 magnets. Number of defective magnets each lot is 48, 56, 47, 71, 83, 48, 200, 570, 67, 47, 34, 48, 37, 57, 29, 45, 20, 10 and 30. Calculate the average fractive defective and three sigma control limits P-chart and examine whether the process in control.
- 6. (a) Within the context of overall planning scheduling systems for operations, explining the role of MRP.

Interporent Z. The lead time for X is week, the standard order quantity is 40 and current availability is 35 units.

Interporent availability is 35 units.

Interporent availability is 35 units.

In 10, 15, 15 and 20 units respectively.

In 2, lead time is two weeks, standard quantity is 80 units and current plability is 90 units. A schedule receipt for is due in week 1. Develop complete the records for X and Y.

- The role does forecasting play in the planning process? Demonstrate have aggregate planning and scheduling costs affected by forecast errors.
- the and explain the advantages and initiations of acceptance sampling over 100% inspection.
- (i) Explain the goals and standards of ISO 9000 quality system.

2.